


PFTR[™] ROLLER BEARING FASTENERS




PEM[®] PFTRCS[™] and PFTRFS[™] roller bearing fasteners are easily installed, pre assembled low friction rollers, that give design engineers a more user-friendly option to the high friction of simple slide shelves without incurring the cost of expensive sliding rail assemblies.


- Low-profile bearing can be captivated with either a clinch or flare, creating a cost-effective tray slide method
- Simple installation and ease of design into limited footprint spacing applications
- Supports loads while guiding and positioning components
- Eliminate the need for oil lubricants and loose hardware typically used in drawer sliders
- Self clinching and flaring roller bearing fasteners are easily installed into pre punched or drilled holes in sheets as thin as .040" / 1mm

Fastener drawings and models are available at <u>www.pemnet.com.</u> Custom sizes are available on special order. <u>Contact us</u> for more information.




PEM[®] PFTRCS[™] Self Clinching Roller Bearing Fasteners












Туре	Code) (Sha Ma	-	Sh	in. eet (ness	Sh +.00			C ax.	I No) om.	ן ±.00 ±0.1		No	r m.	Min. Hole to E	e C/L
		Code	in.	mm	in.	mm	in.	mm	in.	mm	in.	mm	in.	mm	in.	mm	in.	mm
PFTRCS	5.0	1.0	.038	0.97	.040	1	.130	3.3	.129	3.28	.154	3.9	.197	5	.177	4.5	.177	4.5
PFTRCS	9.0	1.0	.038	0.97	.040	1	.240	6.1	.239	6.08	.154	3.9	.354	9	.177	4.5	.295	7.5

PEM® PFTRFS™ Flaring Roller Bearing Fasteners









Туре	Fastener Diameter Code	Min. Sheet Thickness Code	(Sha	A ank) om.	Shee Thickn Rang	ess	in S +.00	Size heet)3″ / 8mm	B Max.		_		- 1		D Nom.		E ±.006" / ±0.15mm		T Nom.	
			in.	mm	in.	mm	in.	mm	in.	mm	in.	mm	in.	mm	in.	mm				
PFTRFS	5.0	1.0	.071	1.8	.040047	1 - 1.2	.130	3.3	.129	3.28	.154	3.9	.197	5	.177	4.5				
PFTRFS	9.0	1.0	.071	1.8	.040047	1 - 1.2	.240	6.1	.239	6.08	.154	3.9	.354	9	.177	4.5				

Material and Finish Specifications

		Compone	nt Material	Standa	rd Finishes	For Use in Sheet Hardness	
Туре		300 Series Stainless Steel	Through Hardened Carbon Steel	Passivated and/or Tested per ASTM A380	Semi-bright Electroless Nickel per ASTM B733 ⁽¹⁾	HRB 80 / HB 150 or less ⁽²⁾	
DETROC	Roller Bearing	•		•			
PFTRCS	Retainer ⁽³⁾		•		•	•	
DETDEO	Roller Bearing	•		•		No liveit	
PFTRFS	Retainer ⁽³⁾		•		•	No limit	
Part Number Co	ode for Finishes			None	EN		

(1) See PEM Technical Support section of our web site for related plating standards and specifications.

(2) HRB - Hardness Rockwell "B" Scale. HB - Hardness Brinell.

(3) Fastener retainer is waxed eliminating the need for lubrication.

Custom sizes are available on special order. Contact us for more information.

Installation


Self Clinching Installation

- 1. Prepare properly sized mounting hole in sheet. Do not perform any secondary operations such as deburring.
- 2. Place fastener into the anvil hole and place the mounting hole (preferably the punch side) over the shank of the fastener.
- 3. With installation punch and anvil surfaces parallel, apply squeezing force until the head of the nut comes into contact with the sheet material.

Installation tooling⁽¹⁾

Fastener	HAEGER [®] Pa	art Number	PEMSERTER® Part Number			
Dia. Code	Anvil	Punch	Anvil	Punch		
5.0	H-330-5MM	H-108-0020L	8026559	975200048		
9.0	H-330-9MM	H-108-0020L	8026560	975200048		

(1) <u>Click here</u> for a quote on Haeger® custom installation tooling.



Flaring Installation

- 1. Prepare properly sized straight through mounting hole in sheet.
- 2. Place fastener into the anvil hole and place the mounting hole over the shank of the fastener as shown in diagram.
- 3. Using a punch flaring tool and a recessed anvil, apply squeezing force until the shoulder of the fastener contacts the sheet. As the fastener seats itself in the proper position, the punch tool will flare the extended portion of the shank outward to complete the installation. If installing into a smooth panel, the fastener shank will protrude after installation. Flare may protrude up to 0.5mm Max.

Before Installation After Installation Installation tooling⁽¹⁾ PUNCH PUNCH HAEGER® Part Number **PEMSERTER®** Part Number Fastener Flaring Dia. Code Anvil Punch Anvil Punch 5.0 H-330-5MM H-193-5.0-1.0 8026559 8026557 SHEET SHEET H-330-9MM H-193-9.0-1.0 9.0 8026560 8026558 (1) Click here for a quote on Haeger® custom installation tooling. ANVIL ANVIL

For Additional HAEGER® and PEMSERTER® Tooling Information / Part Numbers



PFTRCS[™] Performance Data⁽¹⁾

					Test Shee	t Material					
Fastener	Test Sheet	Thickness	Cold-Rolled Steel HRB 53								
Diameter Code			Instal	lation	Pus	hout	Side-Load				
	(in.) (mm)		(lbs.)	(kN)	(lbs.)	(N)	(lbs.)	(N)			
5.0	.040	1	1416	6.3	100	445	45	200			
9.0	.040 1		2316	10.3	150	670	85	380			

Part Number	Max. Number of Traveling Cycles	Bearing Load Max.				
	at 200mm/s ⁽²⁾	(lbs.)	(N)			
PFTRCS-5.0-1.0	100	45	200			
PFTRCS-9.0-1.0	210	45	200			

PFTRFS[™] Performance Data⁽¹⁾

								Test Shee	et Material							
Fastener Test Sheet Diameter Thickness		Cold-Rolled Steel HRB 65							Cold-Rolled Steel HRB 60							
Diameter Code	men	incoo	Installation Pushout Side-Load Installation		lation	Pus	hout	Side-Load								
	(in.)	(mm)	(lbs.)	(kN)	(lbs.)	(N)	(lbs.)	(N)	(lbs.)	(kN)	(lbs.)	(N)	(lbs.)	(N)		
5.0	.040	1	0517	0517	0517	11.0	287	1280	83	370	0517	11.0	-	-	-	_
5.0	.047	1.2	2517	11.2	_	-	-	-	2517	11.2	326	1450	105	470		
9.0	.040	1	3215	2015	0015	14.0	342	1520	130	580	3215	0015 14.0	-	-	-	-
9.0	.047	1.2		14.3	_	-	-	-	3210 14.3	5210 14.3	14.3	388	1730	139	620	

Part Number	Max. Number of Traveling Cycles	Bearing Load Max.				
	at 200mm/s ⁽²⁾	(lbs.)	(N)			
PFTRFS-5.0-1.0	100	45	200			
PFTRFS-9.0-1.0	210	45	200			

(1) Published installation forces are for general reference. Actual set-up and confirmation of complete installation should be made by observing proper seating of fastener as described in the installation steps. Other performance values reported are averages when all proper installation parameters and procedures are followed. Variations in mounting hole size, sheet material, and installation procedure may affect performance. Performance testing this product in your application is recommended. We will be happy to provide technical assistance and/or samples for this purpose.

(2) The maximum number of traveling cycles is tested at 200mm/s under 200N load.

All PEM[®] products meet our stringent quality standards. If you require additional industry or other specific <u>quality certifications</u>, special procedures and/or part numbers are required. Please contact your local sales office or representative for further information.

Regulatory <u>compliance information</u> is available in Technical Support section of our website. Specifications subject to change without notice. See our website for the most current version of this bulletin.



North America: Danboro, Pennsylvania USA | E-mail: info@pemnet.com | Tel: +1-215-766-8853 | 800-237-4736 (USA) Europe: Galway, Ireland | E-mail: europe@pemnet.com | Tel: +353-91-751714 Asia/Pacific: Singapore | E-mail: singapore@pemnet.com | Tel: +65-6-745-0660 Shanghai, China: E-mail: china@pemnet.com | Tel: +86-21-5868-3688

Visit our PEMNET™ Resource Center at <u>www.pemnet.com</u> - Technical support e-mail: <u>techsupport@pemnet.com</u>